

## Manual Pull Station

- **Model** : **CL- 402**
- Application : Indoor
- Adopted voltage : DC ~ 18 ~ 28V (DC-24)
- Adopted current : 100 mA
- Function : Push Button Emergency, Phone Jack, Reset Switch, confirmation LED lamp
- Color : Red
- Size : 138 mm x 48 mm
- Weight : 150 g
- Joint volume : DC - 30V 1A



**CL-402**

## Alarm Siren / Strobe



**CL-207L**

- **Model** : **CL-207L**
- Input Voltage Range : 24V DC (12 ~ 30V DC)
- Operation Current : LED : 50 mA (Max : 65mA)
- Strobe : OVER 8,000m cd. (6pcs Super bright LED)
- Sound Output : 100 +- 5dB (at 24V DC)
- Tone Type : ALARM SIREN (CL-207L)
- Operation Temperature : -10° C~ + 60° C
- Continue Operation Test : OVER 72 Hours (at 24V DC)
- Life Test : "ON" 1 minute, "OFF" 30 seconds, Duty Cycles (at 24V DC) Continuously over 500 Hours period
- Color : Red

## Indicating Light



**CL-401**

- **Model** : **CL- 401**
- Consumption Current : 24VDC 60mA / LED 20mA
- Bulb : 30V / 2W LED
- Lamp Cover : Glass or fire-proof plastic
- Lamp Base : Fire-proof plastic
- Weight : Fire-proof plastic : about 70g
- Dimensions : 90mm (Dia.)x70mm (H)
- Color : Red

## Fire Alarm Bell 6"

- **Model** : **CL-406**
- Input Voltage : 24V DC
- Operation Current : 25 mA
- Sound Output : 93dBA@1M
- Movement : Motor, Pinion and Striker
- Movement Features : DC motor, acetal gear wheel, steel striker
- Gong : Steel, secured with phillips screw
- Base Plate : Molded black polycarbonate
- Dimension : 6" (152 mm)
- Color : red



**CL-406**